

## Over current switch, 16A, 1p, type C characteristic

Part no. PLSM-C16-MW Article no. 242206



Similar to illustration

**Delivery program** 

Number of poles  Iripping characteristic  Application  Rated current  Rated switching capacity according to IEC/EN 60898-1  In pole  C Switchgear for residential and commercial applications  kA 10	zemen, program			
Tripping characteristic  Application  Rated current  In A 16  Rated switching capacity according to IEC/EN 60898-1  KA 10	Basic function			Miniature circuit breakers
Application Switchgear for residential and commercial applications  Rated current In A 16  Rated switching capacity according to IEC/EN 60898-1 kA 10	Number of poles			1 pole
Rated current In A 16 Rated switching capacity according to IEC/EN 60898-1 kA 10	Tripping characteristic			C
Rated switching capacity according to IEC/EN 60898-1 kA 10	Application			Switchgear for residential and commercial applications
	Rated current	In	Α	16
DI OM	Rated switching capacity according to IEC/EN 60898-1		kA	10
roduct range	Product range			PLSM

## **Design verification as per IEC/EN 61439**

In	Α	16
P <sub>vid</sub>	W	0
P <sub>vid</sub>	W	2.2
P <sub>vs</sub>	W	0
P <sub>diss</sub>	W	0
	°C	-25
	°C	75
		linear, per +1 °C, results in a 0.5% reduction of current carrying capacity
		Meets the product standard's requirements.
		Meets the product standard's requirements.
		Meets the product standard's requirements.
		Meets the product standard's requirements.
		Meets the product standard's requirements.
		Does not apply, since the entire switchgear needs to be evaluated.
		Does not apply, since the entire switchgear needs to be evaluated.
		Meets the product standard's requirements.
		Does not apply, since the entire switchgear needs to be evaluated.
		Meets the product standard's requirements.
		Does not apply, since the entire switchgear needs to be evaluated.
		Does not apply, since the entire switchgear needs to be evaluated.
		Is the panel builder's responsibility.
		Is the panel builder's responsibility.
		Is the panel builder's responsibility.
		Is the panel builder's responsibility.
		Is the panel builder's responsibility.
		The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
		Is the panel builder's responsibility. The specifications for the switchgear must be
	P <sub>vid</sub> P <sub>vid</sub> P <sub>vs</sub> P <sub>diss</sub>	P <sub>vid</sub> W P <sub>vid</sub> W P <sub>vs</sub> W P <sub>diss</sub> W °C °C

10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

## **Technical data ETIM 6.0**

Circuit breakers and fuses (EG000020) / Miniature circuit breaker (MCB) (EC000042)

Electric engineering, automation, process control engineering / Electrical installation, device / Miniature circuit breaker system (MCB) / Miniature circuit breaker (MCB) (ecl@ss8.1-27-14-19-01 [AAB905011])

		С
		1
		1
А	4	16
V	/	230
k	κA	10
k	κA	10
k	κA	0
k	κA	0
		AC
		3
Н	łz	50 - 60
		No
		No
		3
		2
		1
m	nm	70.5
		Yes
		IP20
		A V kA kA kA Hz