SIEMENS

## Data sheet 8WA1822-7EF76

G fuse link DIN 41662 slow-response Low breaking capacity Rated continuous current 1 A



| | |
|---|---|
| **Model** | |
| **product brand name** | SENTRON |
| **product designation** | G fuse link |
| **design of the product** | time-lag (T) |
| **type of miniature fuse** | glass fuse |
| **General technical data** | |
| **size of the fuse link** | 5 x 20 mm |
| **melting characteristics** | slow acting (T) |
| **type of voltage of the operating voltage** | AC |
| operating voltage rated value | 250 V |
| **Main circuit** | |
| operational current rated value | 1 A |
| **Display and operation** | |
| **product component visual defect indication** | No |
| **Mechanical Design** | |
| **Net Weight** | 1 g |
| **Approvals Certificates** | |

| Environment | General Product Approval | | | other | |
|---|---|---|---|---|---|
| Environmental Confirmations | EAC | Confirmation | CE EG-Konf. | 产品合格 QC PASS | Confirmation |

**Further information**

**Information on the packaging**
https://support.industry.siemens.com/cs/ww/en/view/109813875
**Information for data generation and storage**
https://support.industry.siemens.com/cs/ww/en/view/109995012
**Information- and Downloadcenter (Catalogs, Brochures,…)**
https://www.siemens.com/lowvoltage/catalogs
**Industry Mall (Online ordering system)**
https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=8WA1822-7EF76
**Service&Support (Manuals, Certificates, Characteristics, FAQs,...)**
https://support.industry.siemens.com/cs/ww/en/ps/8WA1822-7EF76
**Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, ...)**
https://www.automation.siemens.com/bilddb/cax_en.aspx?mlfb=8WA1822-7EF76
**CAx-Online-Generator**
https://www.siemens.com/cax
**Tender specifications**
https://www.siemens.com/specifications
**Characteristic curves**
https://curves.simaris.siemens.com/curves/<mmp_prod_noCOMP="HAUPT"></mmp_prod__no>


Subject to change without notice
© Copyright Siemens

**last modified:** 5/26/2025


Subject to change without notice
© Copyright Siemens

Subject to change without notice
© Copyright Siemens