



Item description

For main distribution with separate FI/LS switches for each circuit. It includes all required components for wiring supply terminal blocks and connecting 14 AC circuits and 2 three-phase circuits. Connection of L- and N-conductors for FI/LS switches to the circuits via multilevel installation terminal blocks without disconnection possibility. Separation of N-potentials for insulation resistance measurement via FI/LS switches.

Full Package Content

Quantity	Item Number	Designation
16	2003-7646	Multilevel installation terminal block, N/L/PE, 2.5 (4) mm ² /AWG 12
2	2003-7642	Multilevel installation terminal block, L/L, 2.5 (4) mm ² /AWG 12
1	2003-7692	End and intermediate plate
3	2016-7601	2-conductor supply terminal block for distribution boxes, gray, 16 (25 "f-st") mm ² /AWG 4
1	2016-7604	2-conductor supply terminal block for distribution boxes, blue, 16 (25 "f-st") mm ² /AWG 4
1	2016-7607	2-conductor ground terminal block, green-yellow, 16 (25 "f-st") mm ² /AWG 4
1	2016-7692	End and intermediate plate
2	249-117	End stop, 10 mm/0.394 in wide
1	2009-110	Marking strips, white, 0.5 m
1	793-5566	WMB marker card 1 ... 50 (2x)
1	793-5472	WMB marker card L1, L2, L3, N, PE, L1, L2, L3, N, PE (10x)
1	2002-433	Push-in type jumper bar 1 - 3
1	210-110	Marking pen, for permanent marking



Data

Material Data

Weight	496.516 g
--------	-----------

Subject to changes.