Switch and fusegear - Quadbreak

Fuse switch disconnector

Application

Heavy duty fuse products for use in commercial and industrial environments, providing isolation and traditional fuse protection for electrical loads.

Features

- Rated for 240/415V 50/60Hz
- Ratings 100A, 160A, 200A, 250A, 315A, 400A, 500A, 630A TP&N
- Utilisation category AC20A, AC21A, AC22A, AC23B at rated current, AC23A for ratings up to 160A
- Handle position provides positive contact indication
- Door handle prevents door being opened when switch is ON or padlocked
- Handle padlockable in ON and OFF positions
- Device may be fed to either top or bottom terminals
- Fuse links or copper links supplied as standard

Construction

- All terminals are fully shrouded
- Quick make and break silver plated contacts
- Door interlock has defeat mechanism allowing switch to be closed with door open
- Removable plain gland plates are fitted at top and bottom
- Cabling space may be increased by the addition of the cable boxes
- Lift off door provides greater access for installation and cabling
- Door opens within the width of the unit allowing units to be mounted adjacent
- Neutral is fitted with disconnectable links
- Earthing kit provided as standard
- Easy access to fuse links
- Removable cross rails allow cables to be laid in easily
- Direct front access to terminals without dismantling the mechanism
- Clear shrouds allow easy access for inspection and visual indication of contact position
- Steelwork finished in polyester epoxy powder

Rating AC21/22/23Single pole & switched neutral Switch disconnector fuseThree pole with neutral link Switch disconnector fuseRecomm cable bo63ASQB0632KSQB0632LSQB0633KSQB0633L SQB1002LSQB0633KSQB0633L SQB1003LSQB1003L100ASQB1002KSQB1002LSQB1003KSQB1003LSQB1003L160ASQB1602KSQB1602LSQB1603KSQB1603LSQB1603L200ASQB2002KSQB2002LSQB2003K-SQB203K	
100A SQB1002K SQB1002L SQB1003K SQB1003L SQBX10 160A SQB1602K SQB1602L SQB1603K SQB1603L SQBX16 200A SQB2002K SQB2002L SQB2003K - SQBX25	
100A SQB1002K SQB1002L SQB1003K SQB1003L 160A SQB1602K SQB1602L SQB1603K SQB1603L SQB1603L 200A SQB2002K SQB2002L SQB2003K - SQB2022L	20
200A SQB2002K SQB2002L SQB2003K - SQB2203K -	XCL160
SQBX25	60
	50 -
250A SQB2502K SQB2502L SQB2503K SQB2503L	XCL250
315A – – SQB3153K –	-
400A – – SQB4003K SQB4003L SQBX50	00 XCL400
500A – – SQB5003K SQB5003L	XCL630
630A – – SQB6303K SQB6303L SQBX63	
800A – – – SQB8003L	XCL800

Castell figure locks

Quadbreak can be factory fitted with Castell interlock type FS for locking in off position. To order:

- 1 Specify required unit e.g. SQB2503K
- 2 Add Castle figure lock order suffix EY
- 3 Add Castle key symbol e.g. A

Thus the order reference for a 250A switch disconnector fuse fitted with a Castell lock symbol A is SQB2503KEYA.

