

# VOLTCRAFT®

## VOLTCRAFT® - TOP PERFORMANCE IN EVERY WAY

“For more than 25 years, our product range has been dynamically adapting to the constant changes in the industry. We commit to offering first-class quality to our customers while delivering an excellent cost-performance ratio. This philosophy remains the cornerstone of Voltcraft’s success.”

## LX-10 LUXMETER

CE  
VERSION 07/18

N° 1662853

The Luxmeter LX-10 allows easy and fast illuminance measurement expressed in lux or foot-candle (fc). The meter is useful where certain environmental lighting requirements are important. Examples include workplaces, desks, reading tables, plant breeding and much more.

### FEATURES:

Measuring range 0~199900 Lux / 0~18578 Fc // High precision illumination sensor //

### EQUIPMENT:

Min/max value display // Switchable measuring unit (Lux/Fc) // Hold function // Optional display illumination // Auto Power Off function (can be disabled) // Battery change indicator // Automatic range selection //

### TECHNICAL DATA:

Measuring range	0~199900 Lux / 0~18578 Fc
Basic accuracy	±(4% display value +8 digit)
Resolution	1/10/100 Lux 1/10 Fc
Measuring interval	0.5 s
Voltage supply	3 x 1.5 V micro batteries (AAA)
Dimensions (L x W x H)	163 x 54 x 28 mm
Weight	106 g
Measurement conditions	0 to +60 °C (max. 80% relative air humidity)

### PACKAGE CONTENTS:

Luxmeter LX-10 // 3 micro batteries (AAA) // Operating instructions //



This data sheet is a publication by Conrad Electronic SE, Klaus-Conrad-Str. 1, D-92240 Hirschau (www.conrad.com). All rights including translation reserved. Reproduction by any method, e.g. photocopy, microfilming, or the capture in electronic data processing systems require the prior written approval by the editor. Reprinting, also in part, is prohibited. This publication represent the technical status at the time of printing.  
© Copyright 2018 by Conrad Electronic SE. 1662853\_V2\_0718\_02\_VTP\_ds\_en